

2 Wire Kit

Part # J-2W-BLK-R7



2 wire kit

Consisting of 2 separate cables. Cable 1 containing the earpiece with quick disconnect acoustic tube. Cable 2 contacting the microphone, and PTT (push to talk) switch.

The Microphone/PTT is supplied with sufficient cable to place on the users lapel, or run down the sleeve and mount onto the shirt cuff.

The speaker and acoustic tube can be removed at the DIN plug point. Various other DIN earpieces can be added if users prefer a different style of earpiece.

Product fitted with official R7 GCAI connector.

FEATURES

Low cost solution

Comfortable to wear for long work periods

Microphone/PTT can be worn on lapel, or the shirt cuff

Kevlar reinforced cable

Easy to replace components

Option to alter acoustic tube to alternative style of earpieces

Product Configuration & Technical Details

Microphone type	Directional
Cable length	143cm radio connector to microphone/PTT housing 108cm radio connector to earpiece speaker
Microphone Sensitivity	-58dB
Microphone Range	100Hz – 14kHz
Speaker	Not less than 100mW
Earpiece Style	Quick disconnect acoustic tube (supplied with spare ear tip)
Acoustic Tube	Coiled section 5cm Ear hook to quick disconnect (21cm relaxed, 35cm stretched)
Colour	Black cable
Warranty	12 months